Data sheet for household tumble driers

In acc. with delegated regulation (EU) No. 392/2012

Miele				
Model name/identifier		TSA223WP Active		
Rated capacity ¹	kg	7,0		
	Air-vented /			
Type of tumble drier	condenser	-/•		
Energy efficiency class				
A+++ (most efficient) to D (least efficient)		A++		
Weighted annual energy consumption (AE _c) ²	kWh/year	208		
Tumble drier Automatic	/ non-automatic	• /		
Energy consumption of the standard cotton progr	amme			
Energy consumption at full load	kWh	1,70		
Energy consumption at partial load	kWh	0,96		
Weighted power consumption in off-mode (P_o)	W	0,40		
Weighted power consumption in the left-on				
mode (P _i)	W	0,40		
Duration of the 'left-on' mode (T _i) ³	min	15		
Standard programme to which the information in	the			
label and the fiche relates ⁴		Cottons with arrow		
Programme time of the 'standard cotton program	me'			
Weighted programme time	min	121		
Programme time at full load	min	155		
Programme time at partial load	min	95		
Condensation efficiency class ⁵				
A (most efficient) to G (least efficient)		А		
Weighted condensation efficiency for the 'standar	rd cotton			
programme' at full and partial load	%	94		
Average condensation efficiency of the 'standard				
programme' at full load	%	95		
Average condensation efficiency of the 'standard				
programme' at partial load	%	94		
Sound power level (L _{WA}) ⁶	dB(A) re 1 pW	66		
Built-in		-		

Yes, standard feature

¹ In kg of cotton laundry for the standard cotton programme at full load.

² based on 160 drying cycles of the standard cotton programme at full and partial load, and the consumption of the low-power modes. Actual energy consumption per cycle will depend on how the appliance is used.

³ If the household tumble drier is equipped with a power management system.

⁴ This programme is suitable for drying normal wet cotton laundry and is the most efficient programme in terms of energy consumption for cotton.

⁵ If the household tumble drier is a condenser tumble drier.

⁶ For the standard cotton programme at full load.